ONE-LIGHT LED WALL SCONCE

Description:

An elegant white linen shade that is open on the top and bottom diffuses light efficiently. Ideal for vanity and hospitality applications.

Specifications:

- · Brushed Nickel (-009) (plated)
- Steel Construction
- White linen shade
- LED Module is replaceable (part # 93074037)
- 624 lumens 66 lumens/watt (source)

PROGRESS LIGHTING[™]

- 3000K color temperature, 90+ CRI
- Dimmable to 10% brightness (See Dimming Notes)
- + Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- Complies with "Americans with Disabilities Act" ADA
- ENERGY STAR[®] qualified
- · Meets California Title 24 JA8-2016

Performance:

Number of Modules	1
Input Power	9w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	624/66 (LM-82)
Lumens/LPW (Delivered)	302/32.5 (LM-79)
CCT	3000 K
CRI	90+
Life (hours)	60,000 (L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Dry location listed
	ENERGY STAR [®] qualified
	Meets California Title 24 JA8-2016

Project:

Fixture Type: Location:

Contact:

Wall mounted • Dry location listed PROGRESS LED

P710010-009-30

Images:



Dimensions:

Width: 6-3/4" Depth: 4" Height: 12" H/CTR: 6"



ONE-LIGHT LED WALL SCONCE

Wall mounted • Dry location listed PROGRESS LED



Dimming Notes:

P710010 is designed to be compatible with many Triac/Forward Phase or ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P
Lutron Nova T NTELV-300
Lutron Caseta
Lutron Ariadni AY-600P
Leviton Illumatech IPI06-1LZ
Leviton SureSlide 6672
Lutron Ariadni AYCL-153P
Lutron Skylark Contour CTCL-153P
Lutron Diva DVCL-153P
Lutron Toggler TGCL-153P
Lutron Maestro MACL-153M
Lutron Ariadni AYLV-600P
Lutron NOVA T NTLV-600
lutron Maestro MAELV-600
Lutron spacer/system SPSELV-600
Lutron Renoir II AWRMG-EAW
Lutron Nova N-600

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.